

WEATHERPHASE™ ROTARY PHASE CONVERTER

Designed for outdoor use and areas of high moisture and where extreme temperature changes can cause condensation inside unit. This unit is rated open drip proof and does not guard against direct water spray or invasion of foreign matter. 230V models & 460V models available. See chart.

FULL POWER Phase Converter runs 3-phase equipment from single-phase power source at full power.



5HP MODEL SHOWN

- HEAVILY LOADED APPLICATIONS
- MULTI-SPEED APPLICATIONS
- MULTI-MOTOR OPERATION
- RESISTIVE LOADS
- 4 YEAR WARRANTY

***DESIGNED FOR OUTDOOR USE** and areas of high moisture. WeatherPhase™ features rating: Intent of USCG 259 and IEEE 45 (Stainless steel nameplate is stamped USCG 259, IEEE45). Treatment of windings and mechanical parts are for applications outdoors or in areas of high moisture. Motors are double dipped and baked in standard insulating varnish. Pipe tap lead outlet in conduit box. IP Protection IP55. It is important to note this converter is not *waterproof*. This converter is not intended to guard against saltwater corrosion. When used outdoors, we recommend installing inside an enclosure.

Where other specialty specifications are needed, including saltwater corrosion resistance, we offer custom-made Rotary Converters. These require a lead time of about 10 weeks.

- For long, heavy starting loads, instant reversing, momentarily overloaded motors, or for imported equipment, contact factory or refer to application guidelines RTN, or go to <https://phaseconverters.phase-a-matic.com/Asset/RWPB.pdf>.

- **Multiple motor applications:** Due to the high in-rush current required to start a motor (5 to 10 times the normal running current), most applications require sizing the HP of the Rotary Converter 50% larger, **or more** than the horsepower of the largest motor, or any combination of motors started at exactly the same time. The first motor started, **if not running heavily loaded**, generates additional 3-phase power back into the circuit. You can then run additional motors (not heavily loaded and not all started at the same time). A maximum of up to 3 times the HP rating of the Rotary Converter can run at the same time, if not heavily loaded, and not started simultaneously. For example, a 30 HP Rotary Converter potentially could run motors totaling up to 90 HP. Contact factory for verification of sizing.

Rotary Converter WeatherPhase™ Models			
230V "RWP" Models	460V "RHWP" Models*	HP	Shipping Wt. Lbs.
RWP-5	---	5	70
RWP-7	---	7.5	110
RWP-10	---	10	125
RWP-15	RHWP-15	15	255
RWP-20	RHWP-20	20	280
RWP-30	RHWP-30	30	365
RWP-40	RHWP-40	40	460
RWP-50	RHWP-50	50	505
Some models are in stock; * most require lead time.			

- Causes no interference to radio, television, or computer equipment.
- For 50Hz operation consult factory
- F.O.B. Palmdale, California
- For larger sizes, contact factory.

Phase-A-Matic, Inc.

39360 3rd St. E. Suite 301 Toll Free: 800-962-6976
 Palmdale, CA. 93550-3255 Local: 661-947-8485
 Email: info@phase-a-matic.com FAX: 661-947-8764

www.phase-a-matic.com

CAUTION: ALWAYS START CONVERTER BEFORE APPLYING LOAD

- Magnetic controls or single-phase loads (including electronics, microprocessors, etc.) must always be energized by lines T1 and T2.
- Never connect a ground or neutral to line T3 (manufactured phase), which can easily be identified as the line with the highest voltage to ground with the converter running. Properly ground all electrical equipment.
- It is essential that careful consideration be given to your wiring length and size to prevent slow starting due to a voltage drop. Consult the National Electrical Code for proper wire sizing.
- Due to the high starting current (in-rush current) common to electric motors, a drop of starting torque may occur when using a converter that is too small. Because of this, it is NOT advised to size an application HP for HP. Most applications require sizing the converter 50% larger or more than the largest HP rated motor of your equipment.

MODEL		LARGEST MOTOR HP <small>See #A below</small>	MULTIPLE MOTORS LIGHTLY LOADED <small>See #B below</small>	ROTARY CONVERTER IDLE CURRENT AMPERAGE <small>(Approximate)</small>		DISCONNECT SWITCH TIME DELAY FUSE AMPERAGE		NEMA STARTER SIZE		MAGNETIC STARTER THERMALS OVERLOADS AMPERAGE		MINIMUM SINGLE-PHASE SUPPLY BREAKER AMPS <small>See #C below</small>		SHIPPING DIMENSIONS <small>In inches</small>
230V	*460V	230V/460V	230V/460V	230V	460V	230V	460V	230V	460V	230V	460V	230V	460V	230V/460V
RWP-5	RHWP-5	3	15 HP	3	1.5	30	15	1	1	15.9	8	30	15	19 x 12 x 13
RWP-7	---	5	22 HP	5	---	40	---	1	---	26	---	40	---	16 x 16 x 16
RWP-10	---	6	30 HP	7	3.5	45	30	2	2	35	17.5	60	30	16 x 16 x 16
RWP-15	RHWP-15	10	45 HP	8	4	60	30	3	3	48	24	100	50	31 x 24 x 21
RWP-20	RHWP-20	12	60 HP	10	5	80	40	3	2	63	35	125	60	31 x 24 x 21
RWP-30	RHWP-30	20	90 HP	12	6	125	60	3	3	94	48	200	100	31 x 24 x 21
RWP-40	RHWP-40	25	120 HP	13	8	150	80	3	3	117	63	250	125	31 x 24 x 24
RWP-50	RHWP-50	30	150 HP	15	9	200	100	4	3	145	78	300	150	31 x 24 x 24

A. LARGEST MOTOR HP: Almost all machines require sizing the converter 50% larger or more than the largest HP motor of your machine. See #4 above.

B. MULTIPLE MOTORS LIGHTLY LOADED: HP shown in chart reflects maximum HP allowable under specific conditions. Example: Multiple machinery, not started at the same time, and that is running lightly loaded. For larger sizes consult factory.


C. MINIMUM SINGLE-PHASE SUPPLY: Single-phase supply shown is for absolute maximum output of the Rotary Converter. Most of the time the converter is oversized to provide the high starting current for the motor. It is not always necessary to size the single-phase breakers this large. Contact Phase-A-Matic for smaller single-phase breaker qualifications.

IMPORTANT: This chart is simplified and cannot reflect the many types of applications possible. Contact Phase-A-Matic, Inc. at 1-800-962-6976 to verify your phase converter requirements.

Larger horsepower phase converter systems may be obtained by connecting multiple Rotary Converters in parallel. This is necessary for models that are larger than 100 HP. Contact Phase-A-Matic, Inc. for wiring illustration for multiple units banked together. Or see it on our web site at: <http://www.phase-a-matic.com>. Go to Rotary Converter and see Installation.

*460V "RHWP" Models require lead time.

- Table shows approximate idle current at 230V for 230V models, 460V for 460V models. Higher line voltage will cause idle current to increase. Excessive amperage could also be caused by incorrect installation.
- For converters with grease fittings, lubricate every 12 months for normal operation, or every 6 months for continuous (24-hour) operation. Use high-temp bearing grease: "Exxon POLYREXEM" polyurea grease or equivalent, available from Phase-A-Matic, Inc.
- Voltage sensitive equipment (CNC/PLC, 3-phase powered electronics, etc.) may require a Phase-A-Matic Voltage Stabilizer designed to reduce phase voltage imbalance. Refer to Voltage Stabilizer brochure or call 800-962-6976.
- Converter should reach full speed within 2 to 3 seconds.
- Voltage is 230V single-phase in and 230V three-phase out on 230V models; 460V single-phase in and 460V three-phase out on 460V models.
- Outdoor Use: Install inside a ventilated enclosure.
- Line T-3 amperage increases as load on motor increases and may measure lower than lines T-1 and T-2. This is normal when machine is not fully loaded, or when the machine is engineered with a motor that is amply sized, never realizing full load.



CAUTION: There should be protection from, or avoidance of, flammable or combustible materials around converters as they can eject flame and/or metal in the event of an insulation failure.